



DESCRIPTION

The Belar **FMHD-1** is a state of the art HD Radio monitor designed to support the needs of today’s broadcaster well into the future. The monitor decodes the HD Radio signal and analog FM signal simultaneously displaying HD Radio status, data, time alignment, and configuration information, as well as total, rds, pilot, L, R, L+R and L-R metering and RF spectrums. The **FMHD-1** is a two rack unit with a 640 x 240 wide viewing angle color LCD display and rotary encoder providing a detailed, clean and simple user interface.



The **FMHD-1** currently supports monitoring multiple audio streams and simultaneous monitoring of four streams with optional Decoder Expansion Board and additional decoders. The units 8, user assignable, analog audio outputs, and 3 assignable AES-3ID

outputs provide support for a wide variety of broadcast scenarios including multi-casting and Surround Sound.

In addition to an antenna input for monitoring off the air, the **FMHD-1** has two high level RF inputs for transmitter site operation. The dual RF inputs allow for monitoring at installations using two transmitters to generate the combined Analog/HD signal.

Older wideband Analog FM monitors out in the field may require pre-filtering in order to remove HD radio sidebands. The **FMHD-1** provides two variable bandwidth, high quality filtered analog composite outputs for driving these monitors eliminating interference.

The **FMHD-1** has both RJ-45 10/100 Base-T Ethernet and USB computer interfaces. When used in conjunction with the Wizard for Windows software the **FMHD-1** can be accessed remotely with various PC graphing and logging functions available. The unit also provides 4 user assignable relay closures and email addresses used to indicate alarm conditions.

Supports Belar’s Automatic Delay Correction Software Module

Specifications are subject to change without prior notice.



BELAR ELECTRONICS LABORATORY, INC.

1140 MCDERMOTT DRIVE, SUITE 105 • WEST CHESTER, PA 19380-4043 USA
 PO BOX 1689 • WEST CHESTER, PA 19380-0055 USA
 VOICE (610) 687-5550 • FAX (610) 687-2686
<http://www.belar.com/> • sales@belar.com • service@belar.com • parts@belar.com



FEATURES

- Frequency Agile Antenna and High Level RF Inputs
- RF Spectrum Analysis with Mask and Sideband Power Measurements
- Metering of Analog Total, RDS, Pilot, L, R, L+R, and L-R
- Metering of HD Radio L, R, L+R, L-R Audio
- Support for simultaneous decoding of 4 HD audio streams.
- Time Alignment Graphic Display with Audio Polarity
- Level Alignment Graphic Display Analysis ± 20.0 dB
- HD Radio Control and Status Information
- HD Radio SIS and PAD Data
- BER (Bit Error Rate) Measurements
- Supports Belar’s Automatic Delay Correction Software Module

SPECIFICATIONS

RF Input

Antenna Input 87.5 to 108 MHz frequency agile,
75 Ω , F-Type Connector
RF Inputs 87.5 to 108 MHz frequency agile,
1 to 10 Vrms, 50 Ω , BNC Connector

Composite Outputs

Analog (2 buffered) +1.5 Vrms @ 100%, 75 Ω
unbalanced, BNC Connector
Digital (2 buffered) LVDS, 100 Ω ,
RJ-45 Connector

Audio Outputs

Analog (8 channels assignable) +10 dBm, 600 Ω
balanced, XLR Connector
AES-3ID (6 channels assignable) 1.0 Vp-p
75 Ω , BNC Connector
Headphone (L/R assignable) 1/4” phone jack

Computer Interface

USB Port
Ethernet 10/100 Base-T RJ-45 Connector

Alarms

Relays (4 Assignable) Form C,
15-pin D Connector

Dimensions 19"x3.5"x14.5" (48.26x8.89x36.83 cm),
2 EIA Rack Units
Power Requirements 40 Watts, 90-264V, 47 to 63 Hz
Shipping Weight 15 lbs (6.8 kg)
Shipping Carton 22"x22"x9" (55.9x55.9x22.9 cm)

Specifications are subject to change without prior notice.



BELAR ELECTRONICS LABORATORY, INC.

1140 MCDERMOTT DRIVE, SUITE 105 • WEST CHESTER, PA 19380-4043 USA
PO BOX 1689 • WEST CHESTER, PA 19380-0055 USA
VOICE (610) 687-5550 • FAX (610) 687-2686
<http://www.belar.com/> • sales@belar.com • service@belar.com • parts@belar.com